

## Product No: MS116-0.63

### ABB MS116-0.63 MANUAL MOTOR STARTER 0.40 ... 0.63 A MS116-0.63



#### General Information

Brand	ABB
Product Type	Manual Motor Starter

#### Technical Attributes

Design of Control Element	Turn Button
Breaking Capacity 400V AC - I <sub>cu</sub> (kA)	100
Main Circuit Electrical Connection	Screw Connection
No. of Poles	3
Overload Release Current Setting (A)	0.4
Phase Failure Sensitive	Yes
Power Loss (W)	5.1
Rated Instantaneous Short-Circuit Current - I <sub>i</sub> (A)	7.9
Rated Insulation Voltage (V)	690
Rated Operational Current (A)	0.63
Rated Operational Power AC-3 400V (kW)	0.18
Rated Operational Voltage (V)	690
Rated Uninterrupted Current - I <sub>u</sub> (A)	0.63
Switching Type	Thermomagnetic
Terminal Type	Screw Terminals
Thermal Current Setting Range (A)	0.40 - 0.63
Thermal Overload Protection	Yes

## Dimensions

Dimensions (mm)	45W x 90H x 85.6D
-----------------	-------------------

---

## Protection & Standards

Degree of Protection	IP20
----------------------	------

---

## Resources

Product catalogue (Flipbook)	<a href="#">Download from here</a>
------------------------------	------------------------------------

---