

Product No: MS132-16B

ABB MS132-16B MANUAL MOTOR STARTER 10 ... 16 A MS132-16B

FEATURES

- Compact design, ideal for installations with limited space
- Clear fault indication in a separate window for short-circuit tripping
- Suitable for both 3 phase and single phase applications
- Lockable rotary handle to prevent unauthorized changes
- Designed in compliance with IEC standards



General Information

Brand	ABB
Product Type	Manual Motor Starter
Series	MS132-B

Technical Attributes

Design of Control Element	Turn Button
Breaking Capacity 400V AC - Icu (kA)	100
Main Circuit Electrical Connection	Screw Connection
No. of Poles	3
Overload Release Current Setting (A)	10
Phase Failure Sensitive	Yes
Power Loss (W)	8.4
Rated Instantaneous Short-Circuit Current - Ii (A)	240
Rated Insulation Voltage (V)	690
Rated Operational Current (A)	16
Rated Operational Power AC-3 400V (kW)	7.5
Rated Operational Voltage (V)	250
Rated Uninterrupted Current - Iu (A)	16
Switching Type	Thermomagnetic
Terminal Type	Screw Terminals
Thermal Current Setting Range (A)	10 - 16
Thermal Overload Protection	Yes

Dimensions

Dimensions (mm)	45W x 97.8H x 86.55D
-----------------	----------------------

Protection & Standards

Degree of Protection	IP20
----------------------	------