

Product No: MS132-1.6

ABB MS132-1.6 MANUAL MOTOR STARTER 1.0 ... 1.6 A MS132-1.6



General Information

Brand	ABB
Product Type	Manual Motor Starter

Technical Attributes

Design of Control Element	Turn Button
Breaking Capacity 400V AC - I _{cu} (kA)	100
Main Circuit Electrical Connection	Screw Connection
No. of Poles	3
Overload Release Current Setting (A)	1
Phase Failure Sensitive	Yes
Power Loss (W)	5.1
Rated Instantaneous Short-Circuit Current - I _i (A)	20
Rated Insulation Voltage (V)	690
Rated Operational Current (A)	1.6
Rated Operational Power AC-3 400V (kW)	0.55
Rated Operational Voltage AC (V)	690
Rated Operational Voltage DC (V)	250
Rated Uninterrupted Current - I _u (A)	1.6
Switching Type	Thermomagnetic
Terminal Type	Screw Terminals
Thermal Current Setting Range (A)	1.00 - 1.60
Thermal Overload Protection	Yes

Dimensions

Dimensions (mm)	45W x 90H x 86.75D
-----------------	--------------------

Protection & Standards

Degree of Protection	IP20
----------------------	------

Resources

Product catalogue (Flipbook)	Download from here
------------------------------	------------------------------------
