

Product No: MS132-0.4

ABB MS132-0.4 MANUAL MOTOR STARTER 0.25 ... 0.40 A MS132-0.4



General Information

Brand	ABB
Product Type	Manual Motor Starter

Technical Attributes

Design of Control Element	Turn Button
Breaking Capacity 400V AC - I _{cu} (kA)	100
Main Circuit Electrical Connection	Screw Connection
No. of Poles	3
Overload Release Current Setting (A)	0.25
Phase Failure Sensitive	Yes
Power Loss (W)	5.1
Rated Instantaneous Short-Circuit Current - I _i (A)	5
Rated Insulation Voltage (V)	690
Rated Operational Current (A)	0.4
Rated Operational Power AC-3 400V (kW)	0.09
Rated Operational Voltage AC (V)	690
Rated Operational Voltage DC (V)	250
Rated Uninterrupted Current - I _u (A)	0.4
Switching Type	Thermomagnetic
Terminal Type	Screw Terminals
Thermal Current Setting Range (A)	0.25 - 0.40
Thermal Overload Protection	Yes

Dimensions

Dimensions (mm)	45W x 90H x 86.75D
-----------------	--------------------

Protection & Standards

Degree of Protection	IP20
----------------------	------

Resources

Product catalogue (Flipbook)	Download from here
------------------------------	------------------------------------
