

PRODUCT-DETAILS

## WA4-96-13 WA4-96-13 100-250V50/60HZ-DC Mechanical Latching Unit



General Information

WA4-96-13
1SBN040200R1013
3471523131125

Catalog Description WA4-96-13 100-250V50/60HZ-DC Mechanical Latching Unit

WA4-96-13 is a mechanical latching unit for AF80 and AF96 contactors ensuring that the contactor remains switched on even if there is a lack or a failure of voltage, in application such as energy conservation. Standard contactors can be easily converted into compact latched contactors. The WA4 block contains a mechanical latching device with electromagnetic impulse unlatching (AC or DC) or manual unlatching. Select quickly the WA4 coil thanks to an unlimited choice of control voltages (e.g. 100, 110,

Select quickly the WA4 coil thanks to an unlimited choice of control voltages (e.g. 100, 110, 115, 120, 125, 127, 208, 220, 230, 240 V 50/60 Hz - DC) included inside a large range of voltages from 100 to 250 V 50/60 Hz - DC.

• Extend your auxiliary control circuit by adding additional 1-pole front mounted CA4 and 2pole side mounted CAL4 auxiliary contact blocks

• Design easily your installation with 25% less depth required in panel mounting

 Reduce your stock and increase your solution proposal with 50% of less variants required compared to conventional solutions.

## Ordering

Long Description

 Minimum Order Quantity
 1 piece

 Customs Tariff Number
 85389099

 Product Main Type
 Accessories for Block Contactors

WA4-96-13 2

Popular Downloads		
Instructions and Manuals	1SBC101046M6801	
CAD Dimensional Drawing	2CDC001079B0201	
Dimensions		
Product Net Width	19.8 mm	
Product Net Depth / Length	67.4 mm	
Product Net Height	41 mm	
Product Net Weight	0.065 kg	
Technical		
Coil Consumption	Pull-in DC (Umin / Umax) 15 100 W	
Connecting Capacity Control Circuit	Flexible with Ferrule 1/2x 0.75 2.5 mm² Flexible with Insulated Ferrule 1x 0.75 2.5 mm² Flexible with Insulated Ferrule 2x 0.75 1.5 mm² Rigid Solid 1/2x 1 2.5 mm² Rigid Stranded 1/2x 1 2.5 mm²	
Rated Control Circuit Voltage (U <sub>c</sub> )	50 Hz 100 250 V 60 Hz 100 250 V DC Operation 100 250 V	
Rated Frequency (f)	Control Circuit 50 / 60 Hz	
Rated Insulation Voltage $(U_i)$	acc. to IEC 60947-5-1 690 V	
Standards	IEC/EN 60947-4-1, UL 60947-1, UL 60947-4-1, CSA C22.2 No. 60947-1-13, CSA C22.2 No. 60947-4-1-14	
Suitable For	AF80 AF96	
Terminal Type	Screw Terminals	
Tightening Torque	Control Circuit 1.2 N·m	
Wire Stripping Length	Control Circuit 10 mm	
Technical UL/CSA		
Tightening Torque UL/CSA	Control Circuit 11 in·lb	
Environmental		
Conflict Minerals Reporting Template (CMRT)	9AKK108467A5658	
Maximum Operating Altitude Permissible	Without Derating 3000 m	
REACH Declaration	2CMT2021-006202	
RoHS Information	2CMT2021-006277	
© 2023 ABB. All rights reserved.	2023/09/28 Subject to chang	e without no

RoHS Status	Following EU Directive 2011/65/EU
WEEE B2C / B2B	Business To Business
WEEE Category	5. Small Equipment (No External Dimension More Than 50 cm)

Certificates and Declarations	
CB Certificate	CB_HU-002678-A1
CCC Certificate	CCC_2018010303063035
CQC Certificate	CQC2018010303063035
Declaration of Conformity - CCC	2020980303000186
Declaration of Conformity - CE	1SBD250020U1000
Declaration of Conformity - UKCA	1SBD250042U1000
EAC Certificate	EAC_RU C-FR ME77 B02940
UL Certificate	UL_20181026-E312527_7_2
UL Listing Card	UL_E312527

Container Information	
Package Level 1 Units	box 1 piece
Package Level 1 Width	72 mm
Package Level 1 Depth / Length	25 mm
Package Level 1 Height	44 mm
Package Level 1 Gross Weight	0.08 kg
Package Level 1 EAN	3471523131125

Classifications	
eClass	V11.1 : 27371392
ETIM 6	EC002498 - Accessories for low-voltage switch technology
ETIM 7	EC002498 - Accessories for low-voltage switch technology
ETIM 8	EC002498 - Accessories/spare parts for low-voltage switch technology
ETIM 9	EC002498 - Accessories/spare parts for low-voltage switch technology
IDEA Granular Category Code (IGCC)	5219 >> Switch part or accessory
UNSPSC	39122221

## Categories

WA4-96-13 4

 $Low\ Voltage\ Products\ and\ Systems\ \rightarrow\ Control\ Products\ \rightarrow\ Contactors\ \rightarrow\ Block\ Contactors\ Accessories$ 

