

## Product No: MS132-20

### ABB MS132-20 MANUAL MOTOR STARTER 16 ... 20 A MS132-20

#### FEATURES

- Compact design, ideal for installations with limited space
- Provides reliable protection against short-circuits, overload and phase failures
- High breaking capacity
- Features a lockable rotary handle with clear switch position indication
- Suitable for both 3 phase and single phase applications



#### General Information

Brand	ABB
Product Type	Manual Motor Starter

#### Technical Attributes

Design of Control Element	Turn Button
Breaking Capacity 400V AC - I <sub>cu</sub> (kA)	100
Main Circuit Electrical Connection	Screw Connection
No. of Poles	3
Overload Release Current Setting (A)	16
Phase Failure Sensitive	Yes
Power Loss (W)	6.9
Rated Instantaneous Short-Circuit Current - I <sub>i</sub> (A)	300
Rated Insulation Voltage (V)	690
Rated Operational Current (A)	20
Rated Operational Power AC-3 400V (kW)	7.5
Rated Operational Voltage AC (V)	690
Rated Operational Voltage DC (V)	250
Rated Uninterrupted Current - I <sub>u</sub> (A)	20
Switching Type	Thermomagnetic
Terminal Type	Screw Terminals

Thermal Current Setting Range (A)	16.0 – 20.0
-----------------------------------	-------------

Thermal Overload Protection	Yes
-----------------------------	-----

### Dimensions

Dimensions (mm)	45W x 97.8H x 86.55D
-----------------	----------------------

### Protection & Standards

Degree of Protection	IP20
----------------------	------

### Resources

Product catalogue (Flipbook)	<a href="#">Download from here</a>
------------------------------	------------------------------------