

Product No: MS132-4.0

ABB MS132-4.0 MANUAL MOTOR STARTER 2.5 ... 4.0 A MS132-4.0



General Information

| | |
|--------------|----------------------|
| Brand | ABB |
| Product Type | Manual Motor Starter |

Technical Attributes

| | |
|--|------------------|
| Design of Control Element | Turn Button |
| Breaking Capacity 400V AC - I _{cu} (kA) | 100 |
| Main Circuit Electrical Connection | Screw Connection |
| No. of Poles | 3 |
| Overload Release Current Setting (A) | 2.5 |
| Phase Failure Sensitive | Yes |
| Power Loss (W) | 5.4 |
| Rated Instantaneous Short-Circuit Current - I _i (A) | 50 |
| Rated Insulation Voltage (V) | 690 |
| Rated Operational Current (A) | 4 |
| Rated Operational Power AC-3 400V (kW) | 1.5 |
| Rated Operational Voltage AC (V) | 690 |
| Rated Operational Voltage DC (V) | 250 |
| Rated Uninterrupted Current - I _u (A) | 4 |
| Switching Type | Thermomagnetic |
| Terminal Type | Screw Terminals |
| Thermal Current Setting Range (A) | 2.50 - 4.00 |
| Thermal Overload Protection | Yes |

Dimensions

| | |
|-----------------|--------------------|
| Dimensions (mm) | 45W x 90H x 86.75D |
|-----------------|--------------------|

Protection & Standards

| | |
|----------------------|------|
| Degree of Protection | IP20 |
|----------------------|------|

Resources

| | |
|------------------------------|------------------------------------|
| Product catalogue (Flipbook) | Download from here |
|------------------------------|------------------------------------|
