

Product No: MS132-10

ABB MS132-10 MANUAL MOTOR STARTER 6.3 ... 10 A MS132-10

FEATURES

- Compact design, ideal for installations with limited space
- Provides reliable protection against short-circuits, overload and phase failures
- High breaking capacity
- Features a lockable rotary handle with clear switch position indication
- Suitable for both 3 phase and single phase applications



General Information

Brand	ABB
Product Type	Manual Motor Starter

Technical Attributes

Design of Control Element	Turn Button
Breaking Capacity 400V AC - I _{cu} (kA)	100
Main Circuit Electrical Connection	Screw Connection
No. of Poles	3
Overload Release Current Setting (A)	6.3
Phase Failure Sensitive	Yes
Power Loss (W)	6
Rated Instantaneous Short-Circuit Current - I _i (A)	150
Rated Insulation Voltage (V)	690
Rated Operational Current (A)	10
Rated Operational Power AC-3 400V (kW)	4
Rated Operational Voltage AC (V)	690
Rated Operational Voltage DC (V)	250
Rated Uninterrupted Current - I _u (A)	10
Switching Type	Thermomagnetic
Terminal Type	Screw Terminals

Thermal Current Setting Range (A)	6.30 - 10.0
-----------------------------------	-------------

Thermal Overload Protection	Yes
-----------------------------	-----

Dimensions

Dimensions (mm)	45W x 90H x 86.75D
-----------------	--------------------

Protection & Standards

Degree of Protection	IP20
----------------------	------

Resources

Product catalogue (Flipbook)	Download from here
------------------------------	------------------------------------