

## Product No: MS116-4.0

### ABB MS116-4.0 MANUAL MOTOR STARTER 2.5 ... 4.0 A MS116-4.0



#### General Information

Brand	ABB
Product Type	Manual Motor Starter

#### Technical Attributes

Design of Control Element	Turn Button
Breaking Capacity 400V AC - I <sub>cu</sub> (kA)	75
Main Circuit Electrical Connection	Screw Connection
No. of Poles	3
Overload Release Current Setting (A)	2.5
Phase Failure Sensitive	Yes
Power Loss (W)	5.4
Rated Instantaneous Short-Circuit Current - I <sub>i</sub> (A)	50
Rated Insulation Voltage (V)	690
Rated Operational Current (A)	4
Rated Operational Power AC-3 400V (kW)	1.5
Rated Operational Voltage (V)	690
Rated Uninterrupted Current - I <sub>u</sub> (A)	4
Switching Type	Thermomagnetic
Terminal Type	Screw Terminals
Thermal Current Setting Range (A)	2.50 - 4.00
Thermal Overload Protection	Yes

## Dimensions

Dimensions (mm)	45W x 90H x 85.6D
-----------------	-------------------

---

## Protection & Standards

Degree of Protection	IP20
----------------------	------

---

## Resources

Product catalogue (Flipbook)	<a href="#">Download from here</a>
------------------------------	------------------------------------

---