

Product No: MS132-20T

ABB MS132-20T CIRCUIT BREAKER FOR PRIMARY TRANSFORMER PROTECTION 16 ... 20 A MS132-20T

FEATURES

- Compact design, ideal for installations with limited space
- Provides reliable protection against short-circuits, overload and phase failures
- High inrush current handling
- Built-in capability to manually connect and disconnect transformers from the mains
- The handle is lockable to protect against unauthorized changes



General Information

Brand	ABB
Product Type	Manual Motor Starter

Technical Attributes

Design of Control Element	Turn Button
Breaking Capacity 400V AC - Icu (kA)	100
Indication	Switched-off Indicator
Main Circuit Electrical Connection	Screw Connection
Main Current Circuit Connection Position	Front Side
No. of Poles	3
Overload Release Current Setting (A)	16
Power Loss (W)	4.8
Rated Instantaneous Short-Circuit Current - Ii (A)	400
Rated Uninterrupted Current - Iu (A)	20
Rated Voltage (V)	690

Protection & Standards

Degree of Protection	IP20
----------------------	------