

## Product No: AF263000L13

### ABB CONTACTOR 45A AC1 26A AC3 3P 3NO 100-250VACDC COIL FOR LAMP STARTING AF263000L13

#### FEATURES

- Voltage Rating: 690 V IEC or 600 V UL
- Poles: 3
- Control Voltage Range: 100-250 V AC (50/60 Hz) and DC
- Built-in Surge Protection
- Energy Efficiency: Reduces panel energy consumption
- Designed for Unstable Networks: Ensures reliable operation
- Block Type Design: Easily extendable with auxiliary contact blocks and accessories



#### Technical Attributes

No. of Normally-open Contacts	3
Rated Control Circuit Voltage (V)	50 Hz 100 ... 250 V 60 Hz 100 ... 250 V DC Operation 100 ... 250 V
Rated Frequency (Hz)	Control Circuit 50 / 60 Hz Main Circuit 50 / 60 Hz
Rated Operational Voltage (V)	Main Circuit 690 V
Wire Stripping Length (mm)	Control Circuit 10 mm Main Circuit 14 mm

#### Physical Attributes

Ambient Temperature (°C)	Close to Contactor Fitted with Thermal O/L Relay -25 ... 60 °C Close to Contactor without Thermal O/L Relay -40 ... 70 °C Close to Contactor for Storage -60 ... +80 °C
Net Weight (g)	0.31

#### Dimensions

Height (mm)	86
Length (mm)	86
Width (mm)	45

## Protection & Standards

Standards

IEC/EN 60947-1, IEC/EN 60947-4-1, UL 60947-4-1,  
CSA C22.2 No. 60947-4-1

---